



Purpose: To Create/Enable X over Y Billing options

Step 1. Billing Options Overview

Review the billing plans (normal plans and X over Y plans) that are currently active. To view or edit a billing plan, simply click on the **View/Edit/Delete** button.

By default all (6) billing options are Normal Plans. To create a X over Y plan you will need to delete one of the Normal Plans first. Click on **View/Edit/Delete** button of the billing option that is not in use and click on **Delete This Plan**. The Billing Options screen will now have an option to create a X over Y plan.

Internal Billing Options Setup

Two buttons are displayed in a vertical stack: "Create New Normal Plan" and "Create New XoverY Plan".

Normal Plans

Number	Active	Label	
1	Yes	Plan B	View/Edit/Delete
2	No	Label 2	View/Edit/Delete
3	No	Label 3	View/Edit/Delete
4	No	Label 4	View/Edit/Delete
5	No	Label 5	View/Edit/Delete

XoverY Plans

Number	Active	Label
--------	--------	-------



2. Create X over Y Plan.

To create a new plan click on **New X over Y Plan**

The Setup screen appears for the billing plan (and type) you selected.

Internal Billing Options XoverY Plan Setup

Plan	0
Enable	<input checked="" type="checkbox"/>
Label	<input type="text" value="Plan A"/>
Description of Service	<input type="text" value="256K downstream, 128K upstream"/>
Plan Details	
Plan Cost	<input type="text" value="0.00"/>
Plan Duration (X)	<input type="text" value="2"/>
Time Unit for Plan Duration	
Minute	<input type="radio"/>
Hour	<input checked="" type="radio"/>
Day	<input type="radio"/>
Plan Validity (Y)	<input type="text" value="1"/>
Time Unit for Plan Validity	
Day	<input checked="" type="radio"/>
Week	<input type="radio"/>
Month	<input type="radio"/>
Bandwidth	
Up	<input type="text" value="128"/>
Down	<input type="text" value="256"/>
DHCP Pool	
Private	<input checked="" type="radio"/>
Public	<input type="radio"/> <small>NOTE: Public option requires IP Upsell to be turned on. Otherwise, subscribers will receive private IP addresses.</small>
<input type="button" value="Submit this Plan"/> <input type="button" value="Delete this Plan"/> <input type="button" value="Reset"/>	
<small>NOTE: Usernames will be enabled if you submit an XoverY plan.</small>	
<input type="button" value="Back"/>	



1. Click on the **Enable** check box to enable (make active) this billing
2. Define a “label” for this billing plan in the **Label** field.
Each plan must have a unique label, different from other plans.
3. Enter a description for this billing plan in the **Description of Service** field.
4. Enter the cost the plan in the **Plan Cost** field.
5. Enter a duration value for this plan in the **Plan Duration (X)** field.
6. Define the “time unit” for the duration value you entered in Step 5. The time unit can be defined as either **Minute, Hour, or Day**.
7. Enter plan validity value for this plan in the **Plan Validity (Y)** field.
8. Define the “time unit” for the plan validity value you entered in Step 7. The time unit can be defined as either **Day, Week, or Month**.
9. Define the **Up (to network)** and **Down (to subscribers)** bandwidth range for this billing plan.
10. Define the DHCP Pool (public or private) -- see following note.

The “public” option requires IP Upsell to be turned on, otherwise subscribers will receive private IP addresses.

11. Click on the **Submit this Plan** button to save your changes and establish this billing plan.



Internal Billing Options Setup

Normal Plans

Number	Active	Label	
1	Yes	Plan B	View/Edit/Delete
2	No	Label 2	View/Edit/Delete
3	No	Label 3	View/Edit/Delete
4	No	Label 4	View/Edit/Delete
5	No	Label 5	View/Edit/Delete

XoverY Plans

Number	Active	Label	
0	Yes	Plan A	View/Edit/Delete

Alternatively, you can click on the **Delete this Plan** button if you want to delete this plan, or click on the **Reset** button if you want to reset all the values to their previous state.

X over Y is also available via XML. Please ask Nomadix Technical Support to obtain XML DTD document.



3. Subscriber experience

Are you a new user? Click this button:

Are you an existing user?
Please enter your user ID and password:

Username:

Password:

Remember my username and password.

Please contact your Network Administrator in case of problems.

Please choose from the following plans.

Plan Name	Price	Features
<input type="radio"/> Normal Plan	USD 9.95 per Day	512K downstream, 256K upstream

How much time of Internet access would you like to purchase?

Plan Name	Price	Features
<input checked="" type="radio"/> X over Y plan	USD 8.95 / 2 Hour for 1 Day	Choose # of hours within 1 day

Contact your service provider with questions.

Please enter a new user ID and password:

Choose a User ID (optional)

Choose a Password (optional)

Retype the Password (if entered above)

Please enter your promotional code.

Please contact your Network Administrator in case of problems.



You will be billed directly by your hotel.
Thank you for your business.

You will be purchasing Internet access with these options:
Plan B USD 8.95

If this is not correct, please go back to the previous page
and make the necessary changes.

Please contact your Network Administrator in case of
problems.