



Purpose: To enable the NSE to bill directly to the Property Management System (PMS) of a Hotel.

Step 1: Enable AAA for New Subscribers

Authentication Authorization and Accounting Settings

AAA Services Enable

Options		Internal Web Server <input checked="" type="radio"/>	External Web Server <input type="radio"/>
SSL Support	<input type="checkbox"/>	Enabled	i
Encrypt only Sensitive Data	<input type="checkbox"/>	Enabled	
Certificate DNS Name	<input type="text"/>		
Portal Page	<input type="checkbox"/>	Enabled	»
Portal XML POST URL	<input type="text"/>		⚠ Caution
Portal XML Post Port	<input type="text" value="80"/>		
Usernames	<input type="checkbox"/>	Enabled	i
New Subscribers	<input checked="" type="checkbox"/>	Enabled	
Relogin After Timeout	<input type="checkbox"/>	Enabled	
Credit Card Service	<input type="checkbox"/>	Enabled	»
Smart Client Support	<input type="checkbox"/>	Enabled	



Step 2: Configure the Billing Options.

Internal Billing Options Setup				Internal Billing Options Plan Setup	
Normal Plans					
Number Active	Yes	Label		Plan	0
0	<input type="checkbox"/>	Hourly Plan	<input type="button" value="View/Edit/Delete"/>	Enable	<input checked="" type="checkbox"/>
1	<input type="checkbox"/>	Public Plan	<input type="button" value="View/Edit/Delete"/>	Label	Hourly Plan
2	<input type="checkbox"/>	Label 2	<input type="button" value="View/Edit/Delete"/>	Description of Service	256K downstream, 128K upstream
3	<input type="checkbox"/>	Label 3	<input type="button" value="View/Edit/Delete"/>	Facebook Login	<input type="checkbox"/>
4	<input type="checkbox"/>	Label 4	<input type="button" value="View/Edit/Delete"/>	Plan Duration	1
5	<input type="checkbox"/>	Label 5	<input type="button" value="View/Edit/Delete"/>	Pricing	
<input type="button" value="New Plan"/>				Free for PMS User	<input type="checkbox"/>
XoverY Plans				Rate Per Minute	0.00
Number Active	Label			Rate Per Hour	5.95
<input type="button" value="New Plan"/>				Rate Per Day	0.00
Subscriber Messages				Rate Per Week	0.00
Introduction Message	Please choose from the following plans:			Rate Per Month	0.00
Offer Message	How much Internet access time would you like to purchase?			Time Unit	
Policy Message	Contact your service provider with questions.			Minute	<input type="radio"/>
Units of Access:				Hour	<input checked="" type="radio"/>
	Minimum:	Maximum:		Private	<input checked="" type="radio"/>
Minute	1	967680		Public	<input type="radio"/>
Hour	1	16128		Class	(none)
Day	1	672		Rate Per Month	0.00
Week	1	96		Time Unit	
Month	1	24		Minute	<input type="radio"/>
Free Billing Options				Hour	<input checked="" type="radio"/>
Default Free Access Time:	7	Days		Day	<input type="radio"/>
Maximum Subscriber Lifetime:	180	Days (Maximum 180 Days)		Week	<input type="radio"/>
Tax Rate				Month	<input type="radio"/>
Tax Rate	0.000	Percent		Wired for Business	<input type="checkbox"/>
Promotional Code Options				Bandwidth	
	Code Definition	Percentage Discount		Maximum Uplink	2048
1		0		Maximum Downlink	5120
2		0		QoS Policy	(no policy)
3		0		DHCP Pool	
4		0		Private	<input checked="" type="radio"/>
5		0		Public	<input type="radio"/>
<input type="button" value="Save"/> <input type="button" value="Restore"/>				Class	(none)
				<input type="button" value="Save this Plan"/> <input type="button" value="Delete this Plan"/> <input type="button" value="Clear"/>	
				<input type="button" value="Back"/>	



Step 3: Select the Port Location Method.

Port-Location Settings

How AG determines where your subscribers are located.

In Room Port Mapping Enabled ▲ Caution

Username

Password

No Port-Location mapping

VLAN IDs

802.1Q two-way

Access Concentrator Query i

Tut Systems Espresso Cascading

Lucent DSL Terminator

Tut MDU Lite Systems Cascading

RFC1493 Compliant Systems Cascading

RiverDelta 1000B

Elastic Networks

IP address:

SNMP community:

SNMP query interval: (minutes) i

[Relogin after migration?](#)

Save

Restore



Step 4: Create the Port Location list.

The Port Location list can be created using one of the following options:

- Add Port Location
- In Room Port Mapping
- Creating and Importing the Location.txt

Sample Port Location List.

List Port-Location Assignments										
Action	Location	Description	Port	State	Billing Modes*	Billing Plans	Provide DHCP	Subnet	Default QoS Policy	Intra-port Communication
Delete	2		2	Charge	RAD	All plans	Enabled	0.0.0.0	(no policy)	Disabled
Delete	3		3	No Charge	RAD	All plans	Enabled	0.0.0.0	(no policy)	Disabled
Delete	1		1	No Charge		All plans	Enabled	0.0.0.0	(no policy)	Disabled
Delete			4	Charge	CC,FB,PMS,RAD	All plans	Enabled	0.0.0.0	(no policy)	Disabled

Step 5: Select the Property Management System.

Property Management System Settings

Setup AG connections to your PMS

PMS services disabled

PMS Redirector [Configure](#)

PMS Port Test Mode

Type of PMS:	Pre-paid	Post-paid		Pre-paid	Post-paid
ASCII Serial Printer	<input type="radio"/>	<input type="radio"/>	Micros Fidelio (Query & Post)	<input type="radio"/>	<input type="radio"/>
Holidex (AutoClerk)	<input type="radio"/>	<input type="radio"/>	Micros Fidelio (Post Only)	<input type="radio"/>	<input type="radio"/>
HOBIC - OSPS	<input type="radio"/>	<input type="radio"/>	Micros Fidelio (Query & Post with TCP/IP)	<input type="radio"/>	<input type="radio"/>
HOBIC - TSPS	<input type="radio"/>	<input type="radio"/>	Micros Fidelio (Post Only with TCP/IP)	<input type="radio"/>	<input type="radio"/>
HOBIC - 1BT2	<input type="radio"/>	<input type="radio"/>	Target IP Address	<input type="text" value=""/>	
HOBIC - TEST	<input type="radio"/>	<input type="radio"/>	Target Port Number	<input type="text" value="0"/>	
HOBIC - RSI	<input type="radio"/>	<input type="radio"/>	FIAS 8.x Compliant	<input type="checkbox"/>	
Type of Access <input type="text" value="L"/>			Disable Registration Number	<input type="checkbox"/>	
No decimal in amount <input type="checkbox"/>			Micros (1700/2000/3700/ /4700/8700 System Software Emulation)	<input checked="" type="radio"/>	<input type="radio"/>
Galaxy (Post Only)	<input type="radio"/>	<input type="radio"/>	Communications System Unit Number (1-64)	<input type="text" value="1"/>	
Marriott	<input type="radio"/>	<input type="radio"/>	Communications System Name	<input type="text" value="NOMADIX"/>	
WFB (Post Only)	<input type="radio"/>	<input type="radio"/>	Store/Revenue Center Number : Internet Access	<input type="text" value="1"/>	
WFB (Query & Post)	<input type="radio"/>	<input type="radio"/>	Store/Revenue Center Number : Other	<input type="text" value="2"/>	
WFB (Name & Room)	<input type="radio"/>	<input type="radio"/>	Match Last Name Only	<input checked="" type="checkbox"/>	
WFB Revenue Code <input type="text" value="1"/>			Skip First Char In Last Name	<input type="checkbox"/>	
FOSSE (Name & Room)	<input type="radio"/>	<input type="radio"/>	OnQ Compliant	<input type="checkbox"/>	
FOSSE Revenue Code <input type="text" value="2"/>			Long name matching	<input type="checkbox"/>	
NH	<input type="radio"/>	<input type="radio"/>			



NOMADIX

The User experience



NOMADIX™

The following plans are available:

Plan Name	Price per Hour	Features
<input checked="" type="radio"/> Bronze	\$5.99	128 service
<input type="radio"/> Silver	\$10.99	256 Service
<input type="radio"/> Gold	\$0.00	1024 Service

How much access would you like to purchase?

You will be billed per hour based upon which plan you select

Please contact your Network Administrator in case of problems



NOMADIX™

Thank you for your business.

You will be purchasing Internet access with these options:
Bronze\$5.99

If this is not correct, please go back to the previous page and make the necessary changes.

You will be billed directly by your hotel.

Please contact your Network Administrator in case of problems